

Panel Schedule - Pii Chargers in Single Phase w/ 208 Vac 3-phase Wye

| Circuit | Phase | Load Type | Voltage | Breaker | Equipment |
|---------|---------|-----------------|---------|---------|----------------|
| 1 | A-B | L3 Charger (1Ø) | 208 V | 200A | EVSE #1 - 30kW |
| 2 | B-C | L3 Charger (1Ø) | 208 V | 200A | EVSE #2 - 30kW |
| 3 | C-A | L3 Charger (1Ø) | 208 V | 200A | EVSE #3 - 30kW |
| 4 | A-B | L2 Charger | 208 V | 60 A | EVSE #4 - 48A |
| 5 | B-C | L2 Charger | 208 V | 60 A | EVSE #5 - 48A |
| 6 | C-A | L2 Charger | 208 V | 60 A | EVSE #6 - 48A |
| 7 | A-B | L2 Charger | 208 V | 60 A | EVSE #7 - 48A |
| 8 | B-C | L2 Charger | 208 V | 60 A | EVSE #8 - 48A |
| 9 | C-A | L2 Charger | 208 V | 60 A | EVSE #9 - 48A |
| 10 | A-B | L2 Charger | 208 V | 60 A | EVSE #7 - 48A |
| 11 | B-C | L2 Charger | 208 V | 60 A | EVSE #8 - 48A |
| 12 | C-A | L2 Charger | 208 V | 60 A | EVSE #9 - 48A |
| 13-17 | — | Spare / Future | — | — | — |
| 18 | A-B-C-N | Subpanel | 208 V | 100 A | Panel Board #2 |

Panel Schedule - Pii Chargers in Three Phase w/ 208 Vac Three-phase Wye

| Circuit | Phase | Load Type | Voltage | Breaker | Equipment |
|---------|-------|-----------------|---------|---------|----------------|
| 1 | A-B-C | L3 Charger (3Ø) | 208V | 125A | EVSE #1 - 30kW |
| 2 | A-B-C | L3 Charger (3Ø) | 208V | 125A | EVSE #2 - 30kW |
| 3 | A-B-C | L3 Charger (3Ø) | 208V | 125A | EVSE #3 - 30kW |
| 4 | A-B | L2 Charger | 208V | 60 A | EVSE #4 - 48A |
| 5 | B-C | L2 Charger | 208V | 60 A | EVSE #5 - 48A |
| 6 | C-A | L2 Charger | 208V | 60 A | EVSE #6 - 48A |
| 7 | A-B | L2 Charger | 208V | 60 A | EVSE #7 - 48A |
| 8 | B-C | L2 Charger | 208V | 60 A | EVSE #8 - 48A |
| 9 | C-A | L2 Charger | 208V | 60 A | EVSE #9 - 48A |
| 10 | A-B | L2 Charger | 208V | 60 A | EVSE #7 - 48A |
| 11 | B-C | L2 Charger | 208V | 60 A | EVSE #8 - 48A |
| 12 | C-A | L2 Charger | 208V | 60 A | EVSE #9 - 48A |
| 13 | A-B | Facility Load | 208V | 80 A | Lighting Panel |
| 14-16 | — | Spare / Future | — | — | — |
| 17 | B-C | Subpanel | 208V | 100 A | Panel Board #2 |
| 18 | A-C | Subpanel | 208V | 100 A | Panel Board #3 |

Panel Schedule - Pii Chargers in Three Phase w/ 240 Vac 3-phase Delta

| Circuit | Phase | Load Type | Voltage | Breaker | Equipment |
|---------|-------|-----------------|---------|---------|----------------|
| 1 | A-B-C | L3 Charger (3Ø) | 240 V | 125A | EVSE #1 - 30kW |
| 2 | A-B-C | L3 Charger (3Ø) | 240 V | 125A | EVSE #2 - 30kW |
| 3 | A-B-C | L3 Charger (3Ø) | 240 V | 125A | EVSE #3 - 30kW |
| 4 | A-B | L2 Charger | 240 V | 60 A | EVSE #4 - 48A |
| 5 | B-C | L2 Charger | 240 V | 60 A | EVSE #5 - 48A |
| 6 | C-A | L2 Charger | 240 V | 60 A | EVSE #6 - 48A |
| 7 | A-B | L2 Charger | 240 V | 60 A | EVSE #7 - 48A |
| 8 | B-C | L2 Charger | 240 V | 60 A | EVSE #8 - 48A |
| 9 | C-A | L2 Charger | 240 V | 60 A | EVSE #9 - 48A |
| 10 | A-B | L2 Charger | 240 V | 60 A | EVSE #7 - 48A |
| 11 | B-C | L2 Charger | 240 V | 60 A | EVSE #8 - 48A |
| 12 | C-A | L2 Charger | 240 V | 60 A | EVSE #9 - 48A |
| 13 | A-B | Facility Load | 240 V | 80 A | Lighting Panel |
| 14-17 | — | Spare / Future | — | — | — |
| 18 | A-C | Subpanel | 240 V | 100 A | Panel Board #2 |

Panel Schedule - Pii Chargers in Three Phase w/ 240 Vac High Leg Delta

| Circuit | Phase | Load Type | Voltage | Breaker | Equipment |
|---------|-------|-----------------|-----------|---------|----------------|
| 1 | A-B-C | L3 Charger (3Ø) | 240 V | 125A | EVSE #1 - 30kW |
| 2 | A-B-C | L3 Charger (3Ø) | 240 V | 125A | EVSE #2 - 30kW |
| 3 | A-B-C | L3 Charger (3Ø) | 240 V | 125A | EVSE #3 - 30kW |
| 4 | A-B | L2 Charger | 240 V | 60 A | EVSE #4 - 48A |
| 5 | B-C | L2 Charger | 240 V | 60 A | EVSE #5 - 48A |
| 6 | C-A | L2 Charger | 240 V | 60 A | EVSE #6 - 48A |
| 7 | A-B | L2 Charger | 240 V | 60 A | EVSE #7 - 48A |
| 8 | B-C | L2 Charger | 240 V | 60 A | EVSE #8 - 48A |
| 9 | C-A | L2 Charger | 240 V | 60 A | EVSE #9 - 48A |
| 10 | A-B | L2 Charger | 240 V | 60 A | EVSE #7 - 48A |
| 11 | B-C | L2 Charger | 240 V | 60 A | EVSE #8 - 48A |
| 12 | C-A | L2 Charger | 240 V | 60 A | EVSE #9 - 48A |
| 13 | A-B | Facility Load | 240 V | 80 A | Lighting Panel |
| 14-17 | — | Spare / Future | — | — | — |
| 18 | A-C-N | Subpanel | 120/240 V | 100 A | Panel Board #2 |

Panel Schedule - Pii Chargers in Single Phase w/ 240 Vac 3-phase Delta

| Circuit | Phase | Load Type | Voltage | Breaker | Equipment |
|---------|-------|-----------------|---------|---------|----------------|
| 1 | A-B | L3 Charger (1Ø) | 240 V | 200A | EVSE #1 - 30kW |
| 2 | B-C | L3 Charger (1Ø) | 240 V | 200A | EVSE #2 - 30kW |
| 3 | C-A | L3 Charger (1Ø) | 240 V | 200A | EVSE #3 - 30kW |
| 4 | A-B | L2 Charger | 240 V | 60 A | EVSE #4 - 48A |
| 5 | B-C | L2 Charger | 240 V | 60 A | EVSE #5 - 48A |
| 6 | C-A | L2 Charger | 240 V | 60 A | EVSE #6 - 48A |
| 7 | A-B | L2 Charger | 240 V | 60 A | EVSE #7 - 48A |
| 8 | B-C | L2 Charger | 240 V | 60 A | EVSE #8 - 48A |
| 9 | C-A | L2 Charger | 240 V | 60 A | EVSE #9 - 48A |
| 10 | A-B | L2 Charger | 240 V | 60 A | EVSE #7 - 48A |
| 11 | B-C | L2 Charger | 240 V | 60 A | EVSE #8 - 48A |
| 12 | C-A | L2 Charger | 240 V | 60 A | EVSE #9 - 48A |
| 13 | A-B | Facility Load | 240 V | 80 A | Lighting Panel |
| 14-17 | — | Spare / Future | — | — | — |
| 18 | B-C | Subpanel | 240 V | 100 A | Panel Board #2 |